



MAINS SUPPLY

LIGHT FITTING

LIVE - Possible colours : Red or Brown — — LIVE
NEUTRAL - Possible colours : Black or Blue — — NEUTRAL



SAFETY INFORMATION: (Please retain for future reference)

- Always turn off the mains supply before commencing the installation of this fitting .
- This is a Class 2 product and does not require an Earth connection – 220-240 Volts – 50Hz AC.
- This product must be installed in accordance with the national building regulations, if in doubt consult a qualified electrician.
- This fitting is suitable for installation in Indoor locations only .
- Do not mount the fitting in a damp atmosphere.
- Do not stare at the operating lamp .
- Ensure sufficient access to the fitting to enable safe maintenance.

LED INFORMATION:

- The fitting has 3 stage dimming function operated from your existing wall switch . 1st stage Switch ON =25% brightness , 2nd stage switch OFF then ON = 50% Brightness , 3rd stage switch OFF then ON =100% brightness.
- The integrated LED lamps are not replaceable, when the LED lamps reach the end of their life the whole luminaire shall be replaced.

AFTERCARE AND MAINTENANCE:

- Always disconnect power supply when servicing or cleaning.
 - Clean only with a dry or slightly damp cloth.
 - Do not use any abrasive cloths or cleaners as this may damage the product
-
- The LED driver and chip board are removable for recycling only, please refer to diagram below. Once removed this fitting must be disposed of in the correct waste stream.

