



1




8



7


SHADE SUPPLIED SEPARATELY



6



4



2


3

5

MAINS SUPPLY

LIGHT FITTING

LIVE - Possible colours : Red or Brown ———— LIVE
 ⊕ EARTH - Un sleeved copper or (Green / Yellow) ———— EARTH ⊕
 NEUTRAL - Possible colours : Black or Blue ———— NEUTRAL



9

SAFETY INFORMATION: (Please retain for future reference)

- Always turn off the mains supply before commencing the installation of this fitting .
- This is a Class I product and requires an Earth connection – 230 (240) Volts – 50Hz AC.
- This product must be installed in accordance with the National Building Regulations, if in doubt consult a competent electrician.
- Do not cover the light source or lamp shade.
- Do not modify or alter any product before or after installation. This will invalidate your warranty and may render the product un-safe.

POSITION

- This fitting is suitable for installation in indoor locations only.
- Suitable for wall mount only.
- Ensure sufficient access to the fitting to enable safe maintenance.

LAMP INFORMATION:

- Use LED lamps Only.
- Dimming of the luminaire is possible when using lamps that are dimmable.

AFTERCARE AND MAINTENANCE:

- Always disconnect power supply when servicing or cleaning.
- Clean only with a dry or slightly damp cloth.
- Do not use any abrasive cloths or cleaners as this may damage the product.

