



1




8




7


SHADE SUPPLIED SEPARATELY



6





4



10
On/Off Switches

MAINS SUPPLY

LIGHT FITTING



9

SAFETY INFORMATION: (Please retain for future reference)

- Always turn off the mains supply before commencing the installation of this fitting .
- This is a Class I product and requires an Earth connection – 230 (240) Volts – 50Hz AC.
- This product must be installed in accordance with the National Building Regulations, if in doubt consult a competent electrician.
- Do not cover the light source or lamp shade.
- Do not modify or alter any product before or after installation. This will invalidate your warranty and may render the product un-safe.

POSITION

- This fitting is suitable for installation in indoor locations only.
- Suitable for wall mount only.
- Ensure sufficient access to the fitting to enable safe maintenance.
- The luminaire should be positioned so that prolonged staring into the luminaire at a distance closer than 0.2m is not exceed.

LAMP INFORMATION:

- Uses LED lamps Only.
- The fitting is not suitable for dimming.


LAMP INFORMATION:

- The LED Module is replaceable.




AFTERCARE AND MAINTENANCE:

- Always disconnect power supply when servicing or cleaning.
- Clean only with a dry or slightly damp cloth.
- Do not use any abrasive cloths or cleaners as this may damage the product.





1



10